

Contactors and Thermal Relays Series 3SC8 & 3SR8

Selection and ordering data

Series 3SR8

	Rated frame current (A)	Current setting range (A)	Matched fuse type		Matched AC contactor	Type code	Order code
			aM (A)	gG (A)			
	25	0.1~0.16	0.25	2	3SC8-09	R8 25/0.16	22875
		0.16~0.25	0.25	2	3SC8-09	R8 25/0.25	22876
		0.25~0.4	1	2	3SC8-09	R8 25/0.40	22877
		0.4~0.63	1	2	3SC8-09	R8 25/0.63	22878
		0.63~1	2	4	3SC8-09	R8 25/1	22879
		1~1.6	2	4	3SC8-09	R8 25/1.6	22880
		1.25~2	4	6	3SC8-09	R8 25/2	22881
		1.6~2.5	4	6	3SC8-09	R8 25/2.5	22882
		2.5~4	6	10	3SC8-09	R8 25/4	22883
		4~6	8	16	3SC8-09	R8 25/6	22884
		5.5~8	12	20	3SC8-09	R8 25/8	22885
		7~10	12	20	3SC8-12	R8 25/10	22886
		9~13	16	25	3SC8-12	R8 25/13	22887
		12~18	20	35	3SC8-18	R8 25/18	22888
		17~25	25	50	3SC8-25	R8 25/25	22889
	36	23~32	40	63	3SC8-32	R8 36/32	22890
		28~36	40	80	3SC8-32	R8 36/36	22891
	93	23~32	40	63	3SC8-40	R8 93/32	22892
		30~40	40	100	3SC8-40	R8 93/40	22893
		37~50	63	100	3SC8-50	R8 93/50	22894
		48~65	63	100	3SC8-65	R8 93/65	22895
		55~70	80	125	3SC8-80	R8 93/70	22896
		63~80	80	125	3SC8-80	R8 93/80	22897
		80~93	100	160	3SC8-95	R8 93/93	22898

Mounting block

	Matechd relay	Type code	Order code
	R8 25	C8 A7D1064	15971
	R8 36	C8 A7D2064	15972
	R8 93	C8 A7D3064	15973